



VK1 D-STAR Connection Information

Here are the Net details you will need:

For those who have VK1 CRARC programming from our web site, select these pre programmed channels: VK1RWN G or similar should be displayed -see below for model differences.

ID-51A – CH 204 ((VK1RWN G)
IC-92AD – CH 13 (VK1RWN G)
IC-91AD – CH 30 (VK1RWN G)
ID-800H – CH 294 (/1RWNG)
ID-880H – CH 212 (VK1RWN G)
IC-2200H – CH 12 (1RWN G)
IC-2820H – CH 204 (VK1RWN G)

These models have VK1 programming ready for download on our Services web page for your convenience.

Manual User Configuration

FREQ: 146.662500
OFFSET: -600 KHZ (-0.6MHZ)
URCALL set to CQCQCQ,
RPT1 set to VK1RWN C
RPT2 set to VK1RWN G

Give it a short name that you will recognise, e.g. "VK1RWN G".

Remote User Configuration (DVAPS, Hot Spots etc)

Connect to VK1RWN Port C

See our [Services](#) page for more DSTAR information.